KCA-WL100 Firmware Update Guide

Introduction

- This guide describes precautions and procedure for updating the KCA-WL100 firmware.
- To update the firmware, Wi-Fi Access Point (AP) connected to the Internet is necessary.
- If an error occurs while updating, KCA-WL100 may not work correctly. Be sure to read precautions and procedure carefully.

Precautions

- Park the vehicle in a safe place before updating. To prevent the battery from running out, keep the engine running.
- Do not turn off the power of KCA-WL100 and the Wi-Fi AP while downloading the firmware. If the firmware is not downloaded successfully, the error message appears. In this case, retry from Step 1.

New Upstate found!	3.21.5	Download
Firmware error! Try to	reboot and do	wnload again.

• Do not turn off the power of KCA-WL100 while updating. If the firmware is not updated successfully, KCA-WL100 may not work correctly.

Target Firmware Version

This updater is for Version 3.21.24* or later. After updating, it will become Version 3.21.25*. (*: W or K) To check the firmware version, see "Check Firmware Version" in Step 3.

Work Flow

- Step 1. Connect KCA-WL100 to Wi-Fi AP.
- Step 2. Update Firmware
- Step 3. Check Firmware Version.

Step1. Connect KCA-WL100 to Wi-Fi AP

Prepare Wi-Fi AP and confirm Service Set Identifier (SSID) and password.

- 1. Turn on the unit that KCA-WL100 is connected to, and select HDMI as input source.
- 2. Switch the connection mode to "Wireless Link"
- 3. Operate the Android device to connect with "KCA-WL100_ XXXXX " via Wi-Fi.
- 4. Open the browser on the Android device and access http://192.168.49.1>.
 - Setting screen appears.
- 5. Touch 奈 .
 - Access point search screen appears.
- 6. Touch "Scan".
 - AP SSID list appears.







🐼 192.168.49.1/cgi-bin/wif
Back
Scan
Se Ind Access
P_s:

<AP menu screen>

7. Select an AP SSID to connect.

- AP menu screen appears.

8. Enter the password if required and touch "Connect".

<AP SSID list screen>

Ľ	192.168.49.1	′cgi-bin/sca	E	192.168.49
Back			Back	
Sca	n Results:		Others	s Team Buff
*****	Others_Team_Buff		BSSID:	
****	C2F-EVA0-2		00:24:a5:14:64:e	18
	106E3E34DB9E		2412Mbz	-y.
***	C2E-MMSoftWiFil		Security:	
			WPA-PSK-TKIF	P+CCMP][WPA2-PSK-
**	NaviArch		TKIP COMPANY	rageog
**	JvcKenwoodQA_g		Password	d:
**	0096123ACA17			
**	W01_240995191993		ASCIT	
**	HWD14_904E2B4026FB		ILX .	
**	C2E-MMSoftWiEi2		Comment	
	00047945851D		Connect	h.
	OD WEE C		<u> </u>	יי <u>) </u>

When connection is made...

-On the Android device, the selected AP SSID is shown in "Saved Access Points" and "Connecting" appears.- On the unit, "Connected to XXX" is shown.



Step2. Update Firmware

- Touch "Back" repeatedly until you get the setting screen.
 If you cannot get the setting screen, retry 3 and 4 in Step1.
- 2. Touch "Submit" in "Firmware Update", and then touch "OK" on the confirmation screen.

<Submit of update screen>



<Confirmation screen>



- The firmware will be updated automatically as follows:
 Downloading firmware. It takes about 30 to 60 seconds depending on the Wi-Fi condition.
 - Updating firmware. It takes about 120 seconds.
 - Re-booting the unit.

<Download the firmware>





Current version
Updating version

Progress of updating After updating is finished, the unit will be re-booted automatically.

Step3. Check Firmware Version

- 1. Perform 1 to 3 of Step1 to display the setting screen.
- 2. Check the firmware version.

